2SC4155

FOR LOW FREQUENCY AMPLIFY APPLICATION SILICON NPN EPITAXIAL TYPE

DESCRIPTION

2SC4155 is a super mini package resin sealed silicon NPN epitaxial transistor,

It is designed for low frequency voltage application.

.

FEATURE

Small collector to emitter saturation voltage.

VCE(sat)=0.3V max


- ●Excellent linearity of DC forward gain.
- Super mini package for easy mounting


APPLICATION

For Hybrid IC,small type machine low frequency voltage Amplify application.

MAXIMUM RATINGS (Ta=25°C)

Parameter	Ratings	Unit	
Collector to Base voltage	50	٧	
Collector to Emitter voltage	50	٧	
Emitter to Base voltage	6	V	
Collector current	100	mA	
Collector dissipation	200	mW	
T _j Junction temperature		°C	
Storage temperature	-55 ~ +150	လူ	
	Collector to Base voltage Collector to Emitter voltage Emitter to Base voltage Collector current Collector dissipation Junction temperature	Collector to Base voltage 50 Collector to Emitter voltage 50 Emitter to Base voltage 6 Collector current 100 Collector dissipation 200 Junction temperature +150	





ELECTRICAL CHARACTERISTICS (Ta=25°C)

Parameter	Symbol	Test conditions	Limits			Unit
Parameter Symbol		rest conditions		Тур	Max	
C to E break down voltage	V(BR)ceo	I _C =100 μ A ,R _{BE} =∞	50	-	-	٧
Collector cut off current	ICBO	V _{CB} =50V, I _E =0mA		ı	0.5	μΑ
Emitter cut off current	IEBO	V_{EB} =4V, I $_{C}$ =0mA	-	-	0.5	μΑ
DC forward current gain	hFE	V_{CE} =6V, I_{C} =1mA	120	-	560	
DC forward current gain	hFE	V_{CE} =6V, I_{C} =0.1mA	70	1	ı	
C to E Saturation Vlotage	VCE(sat)	$\rm I_{C}$ =30mA , $\rm I_{B}$ =1.5mA	-	-	0.3	٧
Gain bandwidth product	fT	V _{CE} =6V, I _E =-10mA	-	200	-	MHz
Collector output capacitance	Cob	V _{CB} =6V, I _E =0mA,f=1MHz		2.0	_	pF

 $\ensuremath{\mathbb{X}}$: It shows hFE classification at right table

Item	Q	R	S	
hFE	120~270	180~390	270~560	



6-41 Tsukuba, Isahaya, Nagasaki, 854-0065 Japan

Keep safety first in your circuit designs!

ISAHAYA Electronics Corporation puts the maximum effort into making semiconductor products better and more reliable, but there is always the possibility that trouble may occur with them. Trouble with semiconductors may lead to personal injury, fire or property damage. Remember to give due consideration to safety when making your circuit designs, with appropriate measures such as (1) placement of substitutive, auxiliary, (2) use of non-farmable material or (3) prevention against any malfunction or mishan.

Notes regarding these materials

- These materials are intended as a reference to our customers in the selection of the ISAHAYA products best suited to the customer's application; they don't convey any license under any intellectual property rights, or any other rights, belonging
- Customer's application; they don't convey any license under any intellectual property rights, or any other rights, belonging ISAHAYA or third party.

 ISAHAYA or third party.

 ISAHAYA Electronics Corporation assumes no responsibility for any damage, or infringement of any third party's rights, originating in the use of any product data, diagrams, charts or circuit application examples contained in these materials.

 All information contained in these materials, including product data, diagrams and charts, represent information on products at the time of publication of these materials, and are subject to change by ISAHAYA Electronics Corporation without notice due to product improvements or other reasons. It is therefore recommended that customers contact ISAHAYA Electronics Corporation or an authorized ISAHAYA products distributor for the latest product information before purchasing product listed
- ISAHAYA Electronics Corporation products are not designed or manufactured for use in a device or system that is used under circumstances in which human life is potentially at stake. Please contact ISAHAYA electronics corporation or an authorized ISAHAYA products distributor when considering the use of a product contained herein for any specific purposes, such as apparatus or systems for transportation, vehicular, medical, aerospace, nuclear, or undersea repeater use.

 The prior written approval of ISAHAYA Electronics Corporation is necessary to reprint or reproduce in whole or in part these
- If these products or technologies are subject to the Japanese export control restrictions, they must be exported under a license from the Japanese government and cannot be imported into a country other than the approved destination. Any diversion or re-export contrary to the export control laws and regulations of Japan and/or the country of destination is prohibited.

 •Please contact ISAHAYA Electronics Corporation or authorized ISAHAYA products distributor for further details on these
- materials or the products contained therein.