RT1N14BX SERIES

(Transistor)

Transistor With Resistor For Switching Application Silicon NPN Epitaxial Type

DESCRIPTION


RT1N14BX is one chip transistor with built-in bias resistor, PNP type is RT1P14BX.

FEATURE

*Built-in bias resistor (R2=10k Ω).


APPLICATION

. Inverted circuit, switching circuit, interface circuit, driver circuit.



OUTLINE DRAWING UNIT:mm RT1N14BC 2.8 0.65 1.5 0.65 1.5 0.65 JEITA: SC-59 JEDEC: Similar to TO-236

Terminal Connector
①:Base
②:Emitter
③:Collector




RT1N14BX SERIES

(Transistor)

Transistor With Resistor For Switching Application Silicon NPN Epitaxial Type

MARKING



MAXIMUM RATING (Ta=25°C)

SYMBOL	PARAMETER -	RATING				
		RT1N14BU	RT1N14BM	RT1N14BC	RT1N14BS	UNIT
V _{CBO}	Collector to Base voltage	50				
V_{EBO}	Emitter to Base voltage	6				
V_{CEO}	Collector to Emitter voltage	50				
Ιc	Collector current	100				
I _{CM}	Peak Collector current	200				
P _C	Collector dissipation(Ta=25°C)	150	20	00	450	mW
Tj	Junction temperature	+150				
Tstg	Storage temperature	−55 ~ +150				

ELECTRICAL CHARACTERISTICS (Ta=25°C)


CVMPOL	PARAMETER	TEST CONDITION	LIMIT			UNIT
SYMBOL		TEST CONDITION	MIN	TYP	MAX	UNIT
$V_{(BR)CEO}$	C to E break down voltage	I _C =100 μ A, R _{BE} =∞	50	_	1	V
I _{CBO}	Collector cut off current	V_{CB} =50V, I $_{E}$ =0	l	ı	0.1	μΑ
I _{EBO}	Emitter cut off current	V_{EB} =5V, I $_{C}$ =0	375	500	725	μΑ
h _{FE}	DC forward current gain	V_{CE} =5V, I $_{C}$ =5mA	30	_	_	_
$V_{CE(sat)}$	C to E saturation voltage	$I_C = 10$ mA, $I_B = 0.5$ mA	_	_	0.3	٧
R_2	Emitter-base resistor	_	7	10	13	kΩ
f⊤	Gain band width product	V_{CE} =6V, I_{E} =-10mA	_	200	_	MHz


RT1N14BX SERIES


(Transistor)


Transistor With Resistor For Switching Application Silicon NPN Epitaxial Type


TYPICAL CHARACTERISTICS (Ta=25°C)













Keep safety first in your circuit designs!

-ISAHAYA Electronics Corporation puts the maximum effort into making semiconductor products better and more reliable, but there is always the possibility that trouble may occur with them. Trouble with semiconductors may lead to personal injury, fire or property damage. Remember to give due consideration to safety when making your circuit designs, with appropriate measures such as (1) placement of substitutive, auxiliary, (2) use of non-farmable material or (3) prevention against any malfunction or mishap.

Notes regarding these materials

- -These materials are intended as a reference to our customers in the selection of the ISAHAYA products best suited to the customer's application; they don't convey any license under any intellectual property rights, or any other rights, belonging ISAHAYA or third party. ISAHAYA Electronics Corporation assumes no responsibility for any damage, or infringement of any third party's rights, originating in the use of any product data, diagrams, charts or circuit application examples contained in these materials.
- All information contained in these materials, including product data, diagrams and charts, represent information on products at the time of publication of these materials, and are subject to change by ISAHAYA Electronics Corporation without notice due to product improvements or other reasons. It is therefore recommended that customers contact ISAHAYA Electronics Corporation or an authorized ISAHAYA products distributor for the latest product information before purchasing product listed herein.
- ISAHAYA Electronics Corporation products are not designed or manufactured for use in a device or system that is used under circumstances in which human life is potentially at stake. Please contact ISAHAYA Electronics Corporation or an authorized ISAHAYA products distributor when considering the use of a product contained herein for any specific purposes, such as apparatus or systems for transportation, vehicular, medical, aerospace, nuclear, or undersea repeater use.
- The prior written approval of ISAHAYA Electronics Corporation is necessary to reprint or reproduce in whole or in part these materials.
- If these products or technologies are subject to the Japanese export control restrictions, they must be exported under a license from the Japanese government and cannot be imported into a country other than the approved destination. Any diversion or re-export contrary to the export control laws and regulations of Japan and/or the country of destination is prohibited.
- Please contact ISAHAYA Electronics Corporation or authorized ISAHAYA products distributor for further details on these materials or the products contained therein.