RT1P144U-T150

Transistor With Resistor For Switching Application Silicon PNP Epitaxial Type


AEC-Q101 Compliance


FEATURE

- Built-in bias resistor (R1=10k Ω ,R2=47k Ω)
- Mini package for easy mounting

APPLICATION


Inverted circuit, switching circuit, interface circuit, driver circuit.





MAXIMUM RATING(Ta=25°C)

SYMBOL	PARAMETER	RATING	UNIT	
$V_{ ext{CBO}}$	Collector to Base voltage	ollector to Base voltage 50		
V_{EBO}	Emitter to Base voltage	6	V	
V_{CEO}	Collector to Emitter voltage	50	>	
V_{IN}	Input voltage	40	>	
$\mathbf{I}_{\mathtt{C}}$	Collector current	100	mA	
\mathbf{I}_{CM}	Peak Collector current	200	mA	
P _c	Collector dissipation	150	mW	
T_{j}	Junction temperature	+150	သိ	
T_{stg}	Storage temperature	−55 ~ +150	°C	




ELECTRICAL CHARACTERISTICS (Ta=25°C)


SYMBOL	PARAMETER	TEST CONDITION	LIMIT			UNIT
			MIN	TYP	MAX	UNIT
$V_{(BR)CEO}$	C to E breakdown voltage	$I_{C}=-100 \mu$ A, $R_{BE}=\infty$	-50	1	_	V
\mathbf{I}_{CBO}	Collector cut off current	$V_{CB}=-50V$, $I_{E}=0$	_	1	-0.1	μΑ
\mathbf{I}_{EBO}	Emitter cut off current	$V_{EB}=-5V$, $I_{C}=0$	-70	-88	-119	μΑ
h_{FE}	DC forward current gain	V_{CE} =-5V, I_{C} =-5mA	50	1	_	1
$V_{CE(sat)}$	C to E saturation voltage	I_{c} =-10mA, I_{b} =-0.5mA	_	-0.1	-0.3	>
$V_{I(ON)}$	Input on voltage	$V_{CE} = -0.2V$, $I_{C} = -5mA$	_	-1.0	-1.8	>
$V_{I(OFF)}$	Input off voltage	$V_{CE} = -5V$, $I_{C} = -100 \mu A$	-0.4	-0.7	_	>
R1	Input resistor	_	7	10	13	kΩ
R2/R1	Resistor ratio	_	4.2	4.7	5.1	
f_T	Gain band width product	$V_{CE}=-6V$, $I_{E}=10$ mA	_	150	_	MHz


RT1P144U-T150


Transistor With Resistor For Switching Application Silicon PNP Epitaxial Type
















Keep safety first in your circuit designs!

-ISAHAYA Electronics Corporation puts the maximum effort into making semiconductor products better and more reliable, but there is always the possibility that trouble may occur with them. Trouble with semiconductors may lead to personal injury, fire or property damage. Remember to give due consideration to safety when making your circuit designs, with appropriate measures such as (1) placement of substitutive, auxiliary, (2) use of non-farmable material or (3) prevention against any malfunction or mishap.

Notes regarding these materials

- -These materials are intended as a reference to our customers in the selection of the ISAHAYA products best suited to the customer's application; they don't convey any license under any intellectual property rights, or any other rights, belonging ISAHAYA or third party. ISAHAYA Electronics Corporation assumes no responsibility for any damage, or infringement of any third party's rights, originating in the use of any product data, diagrams, charts or circuit application examples contained in these materials.
- All information contained in these materials, including product data, diagrams and charts, represent information on products at the time of publication of these materials, and are subject to change by ISAHAYA Electronics Corporation without notice due to product improvements or other reasons. It is therefore recommended that customers contact ISAHAYA Electronics Corporation or an authorized ISAHAYA products distributor for the latest product information before purchasing product listed herein.
- ISAHAYA Electronics Corporation products are not designed or manufactured for use in a device or system that is used under circumstances in which human life is potentially at stake. Please contact ISAHAYA Electronics Corporation or an authorized ISAHAYA products distributor when considering the use of a product contained herein for any specific purposes, such as apparatus or systems for transportation, vehicular, medical, aerospace, nuclear, or undersea repeater use.
- The prior written approval of ISAHAYA Electronics Corporation is necessary to reprint or reproduce in whole or in part these materials.
- If these products or technologies are subject to the Japanese export control restrictions, they must be exported under a license from the Japanese government and cannot be imported into a country other than the approved destination. Any diversion or re-export contrary to the export control laws and regulations of Japan and/or the country of destination is prohibited.
- Please contact ISAHAYA Electronics Corporation or authorized ISAHAYA products distributor for further details on these materials or the products contained therein.