ISA1399AS1

7.5MAX

0.1

0.45

Unit:mm

FOR GENERAL PURPOSE HIGH CURRENT DRIVE APPLICATION SILICON PNP EPITAXIAL TYPE

4.0

OUTLINE DRAWING

3.0

13.0MIN

2.5

14.0

0.

DESCRIPTION

ISA1399AS1 is a silicon PNP epitaxial type transistor designed with High collector current, high voltage. Complementary with ISA3581AS1.

FEATURE

- High collector current. I_{CM} =600mA
- ●High gain band width product. fT=150MHz typ
- ●High V_{CEO}. V_{CEO}=-50V
- •Excellent linearity of DC forward current gain.

APPLICATION

For switching, small type motor drive application.



Symbol	Parameter	Ratings	Unit
Vсво	Collector to Base voltage	-55	V
VEBO	Emitter to Base voltage	-4	V
VCEO	Collector to Emitter voltage	-50	V
I _C	Collector current	-400	mA
I _{CM}	Peak collector current	-600	mA
P。	Collector dissipation	600	mW
Tj	Junction temperature	+150	°C
T _{stg}	Storage temperature	-55 ~ +150	°C

ELECTRICAL CHARACTERISTICS(Ta=25°C)

Parameter	Parameter	Test conditions	Limits			Unit
		Test conditions		Тур	Max	Unit
V(BR)cbo	C to B break down voltage	$I_{\rm C}$ = -10 μ A , $I_{\rm E}$ = 0	-55	-	1	V
V(br)ebo	E to B break down voltage	I_{E} = -10 μ A , I_{C} = 0	-4	-	-	V
V(BR)CEO	C to E break down voltage	$\rm I_{c}$ = –100 μ A , RBE= ∞	-50	-	-	V
Ісво	Collector cut off current	V $_{CB}$ = -25V , I $_{E}$ = 0mA	-	-	-1	μA
IEBO	Emitter cut off current	$V_{EB} = -2V$, $I_C = 0mA$	-	-	-1	μA
hFE※	DC forward current gain	$V_{CE} = -4V$, $I_C = -100mA$	90	-	500	-
VCE(sat)	C to E Saturation Voltage	I _c = -200mA , I _B = -10mA	-	-0.17	-0.5	V
fT	Gain band width product	V_{CE} = -6V , I _E = 10mA	-	150	-	MHz

%) It shows hFE classification in right table.

ltem	D	E	F
hFE item	90~180	150~300	250~500



2 T

> JEITA: JEDEC:

TERMINAL CONNECTER (1): EMITTER

3:BASE


2:COLLECTOR

ISAHAYA ELECTRONICS CORPORATION	


ISA1399AS1

FOR GENERAL PURPOSE HIGH CURRENT DRIVE APPLICATION SILICON PNP EPITAXIAL TYPE

TYPICAL CHARACTERISTICS



BASE TO EMITTER VOLTAGE VBE (V)



COLLECTOR TO EMITTER VOLTAGE VOE (V)

-30

20

10

COMMON EMITTER TRANSFER(2)

ISAHAYA ELECTRONICS CORPORATION



6-41 Tsukuba, Isahaya, Nagasaki, 854-0065 Japan

Keep safety first in your circuit designs!

ISAHAYA Electronics Corporation puts the maximum effort into making semiconductor products better and more reliable, but there is always the possibility that trouble may occur with them. Trouble with semiconductors may lead to personal injury, fire or property damage. Remember to give due consideration to safety when making your circuit designs, with appropriate measures such as (1) placement of substitutive, auxiliary, (2) use of non-farmable material or (3) prevention against any malfunction or mishap.

Notes regarding these materials

These materials are intended as a reference to our customers in the selection of the ISAHAYA products best suited to the customer's application; they don't convey any license under any intellectual property rights, or any other rights, belonging

Customer's application; they don't convey any license under any intellectual property rights, or any other rights, belonging ISAHAYA or third party. ISAHAYA Flectronics Corporation assumes no responsibility for any damage, or infringement of any third party's rights, originating in the use of any product data, diagrams, charts or circuit application examples contained in these materials. •All information contained in these materials, including product data, diagrams and charts, represent information on products at the time of publication of these materials, and are subject to change by ISAHAYA Electronics Corporation without notice due to product improvements or other reasons. It is therefore recommended that customers contact ISAHAYA Electronics Corporation or an authorized ISAHAYA products distributor for the latest product information before purchasing product listed become hereir

ISAHAYA Electronics Corporation products are not designed or manufactured for use in a device or system that is used under circumstances in which human life is potentially at stake. Please contact ISAHAYA electronics corporation or an authorized ISAHAYA products distributor when considering the use of a product contained herein for any specific purposes, such as apparatus or systems for transportation, vehicular, medical, aerospace, nuclear, or undersea repeater use.
The prior written approval of ISAHAYA Electronics Corporation is necessary to reprint or reproduce in whole or in part these

materials.

If these products or technologies are subject to the Japanese export control restrictions, they must be exported under a license from the Japanese government and cannot be imported into a country other than the approved destination. Any diversion or re-export contrary to be export control laws and regulations of Japan and/or the country of destination is prohibited. •Please contact ISAHAYA Electronics Corporation or authorized ISAHAYA products distributor for further details on these

materials or the products contained therein.